

INVERTERS



GV-2000i



GV-3300i



GV-3300iS

*Battery Not Included

KOSHIN Inverter Specification

Model	GV-2000i	GV-3300i	GV-3300iS
Engine	KOSHIN K80-i	KOSHIN K210-V	KOSHIN K210-V
Engine Type	Air-cooled, 4-stroke, OHV, single cylinder		
Displacement	79cc	212cc	212cc
Engine Starter	Recoil Starter	Recoil Starter	Recoil / Electrical Starter
Push Starter	-	-	Auto Choke
Oil Alert System	Standard		
Rated Output	1800 W(VA)	3000 W(VA)	3000 W(VA)
Maximum Output	2000 W(VA)	3300 W(VA)	3300 W(VA)
Rated Frequency	60Hz		
Rated Voltage	120V		
AC Sockets	NEMA 5-20R(GFCI)×1		
		NEMA L5-30R X1	NEMA L5-30R X1
DC Output	-	5V USB (2.1A, 1A)	
Fuel Tank	1.1gal	2.2gal	2.2gal
Continue Running Time @ 1/2 Rated Power	6.0 hr	8.0 hr	8.0 hr
Continue Running Time @ Rated Power	4.0 hr	4.0 hr	4.0 hr
Noise(7m@Rated Power)	≤66dB	≤67dB	≤67dB
Noise(4m@3/4 Rated Power)	91dB	89dB	90dB
Dimension	19.6"×11.8"×18.4"	23.2"×18.7"×20.6"	23.2"×20.0"×24.2"
Weight	48.5lb	97lb	110.2lb
Co sensor	Standard		
Parallel Operation	Standard (Same Output Model)		
Multifunctional Digital Display Meter	•Voltage •Hertz •Output Current A / Output Power VA •Fuel Level •Continuous Running Hours / Total Running Hours. •Alarm (Engine RPM/Short Circuit / High or Low Voltage / High Temperature) •Low Oil Level Indicator / Over Load Indicator / Service Remainder		

■ All model have GFCI protection.



■ Equipped with CO sensor with automatic shutdown



■ MULTI DISPLAY



GV-3300iS only

■ One Push Start (Electric Starter) and auto choke.

